


Title	Outage Probability of One-Source-with-One-Helper Sensor Systems in Block Rayleigh Fading Multiple Access Channels
Author(s)	Song, Shulin; Cheng, Meng; He, Jiguang; Zhou, Xiaobo; Matsumoto, Tad
Citation	IEEE Sensors Journal, 21(2): 2140-2148
Issue Date	2020-08-24
Type	Journal Article
Text version	publisher
URL	<a href="http://hdl.handle.net/10119/16752">http://hdl.handle.net/10119/16752</a>
Rights	This work is licensed under a Creative Commons Attribution 4.0 License. For more information, see <a href="https://creativecommons.org/licenses/by/4.0/">https://creativecommons.org/licenses/by/4.0/</a> . Shulin Song, Meng Cheng, Jiguang He, Xiaobo Zhou, and Tad Matsumoto, IEEE Sensors Journal, 21(2), 2021, pp.2140-2148, DOI:10.1109/JSEN.2020.3018787.
Description	

# Outage Probability of One-Source-With-One-Helper Sensor Systems in Block Rayleigh Fading Multiple Access Channels

Shulin Song, Meng Cheng<sup>ID</sup>, Jiguang He<sup>ID</sup>, *Member, IEEE*, Xiaobo Zhou<sup>ID</sup>, *Senior Member, IEEE*, and Tad Matsumoto<sup>ID</sup>, *Fellow, IEEE*

**Abstract**—Two correlated sources are transmitted over a block Rayleigh fading multiple access channel (MAC), where information recovery from only one of the sources is aimed at, and the other is used as a helper which helps recover the source sequences at the destination. In this article, the successful transmission is defined as in the case the transmission rates satisfy the intersection of both the MAC region and the Slepian-Wolf (SW) region with a helper, referred to as h-SW region, even though it is a sufficient condition. Then, the outage is defined as the average probability that the two regions do not have an intersection. The explicit expressions of the outage probability of the system are derived, in the form of multiple integrals with respect to the probability density function of instantaneous signal-to-noise ratios of each link. To have an in-depth insight regarding the contributions of some special cases to the successful transmission probability, the occurrence probabilities of these cases are also evaluated. The results indicate that outage probabilities decrease as the correlation between the source and helper information increases. The impacts of geometric gains of each link and the correlation of each link's fading variation are also considered. The most significant finding of this article is that h-SW over a MAC improves the throughput efficiency compared to the orthogonal transmission both in independent and correlated block Rayleigh fading channels without sacrificing the outage probability.

**Index Terms**—Helper, multiple access channel, outage probability, Slepian-Wolf theorem.



## I. INTRODUCTION

IN WIRELESS sensor networks (WSNs), as exemplified in the figure in Abstract, multiple sensors track the states of targets, of which topics are, in general, categorized in statistical signal processing [1]. They then transmit the gathered *correlated* data to the fusion center, of which topics belong

to network information theory. The issues of the location identification and tracking of the targets in WSNs have been investigated, e.g. [2], [3]. In this article, we investigate the outage probability of transmissions in the category of network information theory. The links between the sensors and the fusion center suffer from fading, occurring in the wireless propagation process. Since the information sequences obtained by the sensors are correlated, where the transmission rates for lossless recovery should satisfy the Slepian-Wolf (SW) region, they can help each other to retrieve the original information via joint decoding. Multiple access channel (MAC) is known to increase the up-link transmission efficiency, and especially, when used in WSN, it can significantly improve the throughput and reduce latency. In MAC systems, information sequences collected by the sensors are transmitted to the destination simultaneously. However, there arises a problem that if the information sequences are correlated, as in WSN, the SW and MAC regions, referred to as SW-MAC regions, have to intersect for the successful transmission. Even though having an intersection is a sufficient condition [4], it has been widely used in [5], [6] when analyzing the probability of successful transmissions. Reference [5] analyzes the outage probability of

Manuscript received August 5, 2020; accepted August 13, 2020. Date of publication August 24, 2020; date of current version December 16, 2020. This work was supported in part by the Hitachi, Ltd., and in part by the Hitachi Kokusai Electric Inc. The associate editor coordinating the review of this article and approving it for publication was Dr. Qammer H. Abbasi. (*Corresponding author: Shulin Song.*)

Shulin Song and Meng Cheng are with the School of Information Science, Japan Advanced Institute of Science and Technology (JAIST), Nomi 923-1211, Japan (e-mail: shulin.song@jaist.ac.jp; m-cheng@jaist.ac.jp).

Jiguang He is with Centre for Wireless Communications, University of Oulu, 90570 Oulu, Finland (e-mail: jiguang.he@oulu.fi).

Xiaobo Zhou is with the Tianjin Key Laboratory of Advanced Networking, College of Intelligence and Computing, Tianjin University, Tianjin 300350, China (e-mail: xiaobo.zhou@tju.edu.cn).

Tad Matsumoto is with School of Information Science, Japan Advanced Institute of Science and Technology (JAIST), Nomi 923-1211, Japan, and also with Centre for Wireless Communications, University of Oulu, 90570 Oulu, Finland (e-mail: matumoto@jaist.ac.jp).

Digital Object Identifier 10.1109/JSEN.2020.3018787

a two-correlated-source transmission system over independent block Rayleigh fading channels where both the two sources are aimed to be recovered. In [6], the author studies a two-hop multiple access relay cooperative communication system, where the admissible rate region of two correlated MAC sources with an exclusive-or (XOR) helper is investigated over independent and correlated block Rayleigh fading channels. Reference [5], [6] have motivated us to investigate the case where only one-hop MAC with one source to be detected and the other to work as a helper. The SW region with a helper, referred to as h-SW region, is determined by the source and helper entropy, which is fixed. On the contrary, MAC region is determined by the channel capacities, which vary according to the fading variations. Block Rayleigh fading is assumed in this article where the instantaneous signal-to-noise ratio (SNR) of each link does not change during one block, but changes block-by-block.

The main contributions of this article are summarized as follows:

1. The outage probability expression of one source with one helper over a fading MAC is derived in an explicit form. For the ease of the calculations, we use the approximated h-SW region which is known to be yet very accurate [7].
2. The mathematically derived outage probability is verified to be consistent to that obtained through the Monte-Carlo technique.
3. We investigate the outage probabilities over block independent fading channels with the information correlation between the source and the helper. The geometric gains of each link are also taken into account. It is shown that the 2<sup>nd</sup> order diversity can be achieved with large information correlation. Also, lower outage probability can be achieved in the case the geometric gain of the source link is larger than that of the helper link.
4. The occurrence probabilities of three cases are calculated in order to evaluate how significant contributions those cases make to the successful transmission.

5. We make a comparison of the outage probabilities of orthogonal and MAC transmission systems with one source and one helper over correlated block Rayleigh fading channels.

This article is organized as follows. The system model of one source with one helper transmitting over a block Rayleigh fading MAC, investigated in this article, is provided in Section II. In Section III, we first investigate the scenarios that outage happens, of which the average outage probability is derived in an explicit form. Three successful cases (i)-(iii) are considered, and their average occurrence probabilities are derived also in the explicit forms. In Section IV, the performance curves are presented with the geometric gains of each link and the information correlation as parameters. In Section V, the mathematical expressions of the outage probability are further modified to include the correlation of the fading variations of the two links. Finally, Section VI concludes this article with some technical remarks.

## II. SYSTEM MODEL

Two correlated sources represented as  $u_1$  and  $u_2$  are encoded independently, and jointly decoded at the destination,




Fig. 1. Encoder and joint decoder of one correlated source with one helper.

as shown in Fig. 1. The sources are binary, and uniformly distributed. Hence,  $\Pr\{u = 0\} = \Pr\{u = 1\} = 0.5$ , and the entropy of the source is  $H(u_1) = H(u_2) = 1$ , where  $H(p) = -p \log_2(p) - (1-p) \log_2(1-p)$  is the binary entropy function.

In this article, only source  $u_1$  is aimed to be recovered, and  $u_2$  serves as a helper. The sources  $u_1$  and  $u_2$  are correlated, which are represented by the bit-flipping model, as

$$u_1 = u_2 \oplus e, \quad (1)$$

with

$$e = \begin{cases} 1, & \text{with probability } P_e, \\ 0, & \text{with probability } 1 - P_e. \end{cases} \quad (2)$$

The probability that bit-flipping happens is  $P_e \in [0, 0.5]$ , where  $P_e = 0$  and  $P_e = 0.5$  correspond to the correlation being unity and zero, respectively [9].

Transmission links from the source and from the helper to the destination suffer from block Rayleigh fading. The received sequences can be expressed as

$$y_i = \sqrt{P_i} h_i u_i + n_i, \quad (3)$$

where  $i = \{1, 2\}$  denotes specifically the source-destination and the helper-destination links, respectively.  $P_i$  represents the geometric gain, corresponding to the locations of sensors and the destination [8].  $h_i$  represents the channel gain, which can be described as a complex Gaussian variable with  $CN \sim (0, 1)$ ,  $n_i$  is a complex additive white Gaussian noise (AWGN) with  $CN \sim (0, 1)$ . Since the two-dimensional noise variance is normalized to unity, the average SNR is expressed as  $\Gamma_i = P_i$ , and the instantaneous SNR is given by  $\gamma_i = P_i \cdot |h_i|^2$ . For the simplicity, we ignore shadow fading here.

## III. OUTAGE PROBABILITIES

### A. SW and H-SW Rate Regions

Let the rates of the sources  $u_1$  and  $u_2$  be  $R_1$  and  $R_2$ , respectively. According to Shannon's theorem, if the rate is larger than the entropy of the source, the source can be recovered with an arbitrarily small probability of error, when the length of block code  $n \rightarrow \infty$  [10], as

$$\begin{cases} R_1 \geq H(u_1), \\ R_2 \geq H(u_2), \end{cases} \quad (4)$$

where  $u_1$  and  $u_2$  are independent sources. If the two sources are correlated, we can further compress the rates. According to SW theorem,  $u_2$  can provide correlated information to help




Fig. 2. Admissible rate region of two sources  $u_1$  and  $u_2$ , where the black and red solid lines indicate the independent and correlated cases, respectively [11].

recover  $u_1$ , and hence  $R_1$  only needs to be no less than the conditional entropy  $H(u_1|u_2)$ . Similarly,  $R_2 \geq H(u_2|u_1)$ . Moreover, if we consider two links as a whole, the sum rates have to be no less than the joint entropy of two sources for recovering both of them.  $R_1$  and  $R_2$  should satisfy the admissible SW rate region [12], shown in Fig. 2. It can be mathematically expressed as

$$\begin{cases} R_1 \geq H(u_1|u_2), \\ R_2 \geq H(u_2|u_1), \\ R_1 + R_2 \geq H(u_1, u_2), \end{cases} \quad (5)$$

where  $H(u_1|u_2) = H(u_2|u_1) = H(P_e)$ , and  $H(u_1, u_2) = H(u_2) + H(u_1|u_2) = H(u_1) + H(u_2|u_1) = 1 + H(P_e)$  with bit-flipping model. Conversely, the correlation between  $u_1$  and  $u_2$  can be exploited to increase the information recovery probability.

However, since  $u_2$  is utilized as a helper, the admissible rate should satisfy the following expressions [13]

$$R_1 \geq \begin{cases} H(u_1|u_2), & \text{for } R_2 \geq H(u_2), \\ H(u_1, u_2) - R_2, & \text{for } H(u_2|u_1) \leq R_2 \leq H(u_2), \\ H(u_1), & \text{for } 0 \leq R_2 \leq H(u_2|u_1), \end{cases} \quad (6)$$

which is an approximated, yet accurate, expression. The admissible rate region of h-SW is shown in Fig. 3.

### B. MAC Rate Region and Source-Channel Separation

According to Shannon's lossless source-channel separation theorem [14], the transmission rate for point-to-point communications over discrete memoryless channels is given by

$$H(u)R_c \leq C(\gamma), \quad (7)$$

where  $R_c$  indicates the normalized spectrum efficiency including the channel coding rate and the modulation multiplicity. Throughout this article,  $R_c = 0.5$  is assumed without loss of generality.  $C(\gamma) = \log_2(1 + \gamma)$  denotes the channel capacity with the instantaneous SNR  $\gamma$ . The source index  $i$  is ignored in Eq. 7 for the simplicity.

In the same way as in [5], the separation theorem can be further extended to the h-SW and MAC case, as: if the h-SW and MAC regions have an intersection, source-channel




Fig. 3. Approximated admissible rate region of  $u_1$ , while  $u_2$  is utilized as a helper [13].




Fig. 4. Achievable rate region of MAC.

separation holds. However, as stated before, this is a sufficient condition. The achievable MAC rate region is then shown in Fig. 4. The mathematical expressions of the MAC region with the assumption that the separation holds is given by [7]

$$\begin{cases} R_1 R_c \leq C(\gamma_1), \\ R_2 R_c \leq C(\gamma_2), \\ R_1 R_c + R_2 R_c \leq C(\gamma_1 + \gamma_2). \end{cases} \quad (8)$$



### C. Expressions of Outage Probability

To achieve successful transmission of one source with one helper, the sufficient condition requires the MAC and h-SW regions to intersect. In the latter part of this article, this system is referred to as h-SW-MAC system to save the space. Conversely, if the intersection does not happen, as shown in Fig. 5 and Fig. 6, outage happens. Hence, the outage probability can then be calculated by

$$P_{out} = P_{out,1} + P_{out,2}. \quad (9)$$

In Fig. 5, since  $\frac{1}{R_c}C(\gamma_1) < H(u_1|u_2)$ , the MAC and h-SW regions do not intersect. Thus, we have

$$\begin{aligned} P_{out,1} &= \Pr \left\{ \frac{1}{R_c}C(\gamma_1) < H(u_1|u_2) \right\} \\ &= \int_{\Phi(0)}^{\Phi[H(u_1|u_2)]} \int_{\Phi(0)}^{\Phi(+\infty)} p(\gamma_1) p(\gamma_2) d\gamma_2 d\gamma_1 \end{aligned}$$

Fig. 5. Scenario 1 yielding  $P_{out,1}$ .Fig. 6. Scenario 2 yielding  $P_{out,2}$ .

$$\begin{aligned}
 &= \int_0^{2^{R_c H(P_e)} - 1} \int_0^{+\infty} p(\gamma_1) p(\gamma_2) d\gamma_2 d\gamma_1 \\
 &= 1 - \exp \left\{ -\frac{1}{\Gamma_1} \left[ 2^{R_c H(P_e)} - 1 \right] \right\}. \quad (10)
 \end{aligned}$$

In Fig. 6, with  $H(u_1|u_2) \leq \frac{1}{R_c} C(\gamma_1) < H(u_1)$ , the MAC and h-SW regions do not intersect when  $\frac{1}{R_c} C(\gamma_1 + \gamma_2) < H(u_1, u_2)$ . Thus, we have

$$\begin{aligned}
 P_{out,2} &= \Pr \left\{ \begin{aligned} &H(u_1|u_2) \leq \frac{1}{R_c} C(\gamma_1) < H(u_1); \\ &\frac{1}{R_c} C(\gamma_1 + \gamma_2) < H(u_1, u_2) \end{aligned} \right\} \\
 &= \int_{\Phi[H(u_1|u_2)]}^{\Phi[H(u_1)]} \int_{\Phi(0)}^{\Phi[H(u_1, u_2)] - \gamma_1} p(\gamma_1) p(\gamma_2) d\gamma_2 d\gamma_1 \\
 &= \int_{2^{R_c H(P_e)} - 1}^{2^{R_c} - 1} \int_0^{2^{R_c [1 + H(P_e)]} - 1 - \gamma_1} p(\gamma_1) p(\gamma_2) d\gamma_2 d\gamma_1 \\
 &= \exp \left\{ -\frac{1}{\Gamma_1} \left[ 2^{R_c H(P_e)} - 1 \right] \right\} - \exp \left[ -\frac{1}{\Gamma_1} (2^{R_c} - 1) \right]
 \end{aligned}$$




Fig. 7. Admissible h-SW-MAC region of Case (i).

$$\begin{aligned}
 & - \frac{\Gamma_2}{\Gamma_1 - \Gamma_2} \exp \left[ -\frac{1}{\Gamma_1} (2^{R_c} - 1) \right] \\
 & \cdot \exp \left\{ -\frac{1}{\Gamma_2} \left[ 2^{R_c H(P_e) + R_c} - 2^{R_c} \right] \right\} \\
 & + \frac{\Gamma_2}{\Gamma_1 - \Gamma_2} \exp \left\{ -\frac{1}{\Gamma_1} \left[ 2^{R_c H(P_e)} - 1 \right] \right\} \\
 & \cdot \exp \left\{ -\frac{1}{\Gamma_2} \left[ 2^{R_c H(P_e) + R_c} - 2^{R_c H(P_e)} \right] \right\}. \quad (11)
 \end{aligned}$$

The successful transmission probability is given by  $P_{in} = 1 - P_{out}$ .

The function  $\phi(\cdot)$  represents the instantaneous SNR required to transmit rate  $R$  sequence with a Gaussian code book, i.e.

$$\gamma = \phi(R) = 2^{R_c R} - 1. \quad (12)$$

$p(\gamma_i)$  is the probability density function of instantaneous SNR over Rayleigh fading channels, expressed as [15]

$$p(\gamma_i) = \frac{1}{\Gamma_i} \exp \left( -\frac{\gamma_i}{\Gamma_i} \right). \quad (13)$$

### D. Three Cases of Successful Transmissions

To have an in-depth insight of the contributions to the average successful probability  $P_{in}$ , three cases (i) - (iii) defined in the Introduction section are investigated in this subsection.

Case (i):

The admissible rate region in Case (i) is shown in Fig. 7, which corresponds to the situation where  $H(u_1|u_2) \leq \frac{1}{R_c} C(\gamma_1) \leq H(u_1)$  and  $H(u_1, u_2) \leq \frac{1}{R_c} C(\gamma_1 + \gamma_2)$ . When  $\gamma_1 \ll \gamma_2$ , Case (i) happens most likely. The average occurrence probability of the case can be derived mathematically in an explicit form, as

$$\begin{aligned}
 P_{in, case(i)} &= \Pr \left\{ \begin{aligned} &H(u_1|u_2) \leq \frac{1}{R_c} C(\gamma_1) \leq H(u_1); \\ &H(u_1, u_2) \leq \frac{1}{R_c} C(\gamma_1 + \gamma_2) \end{aligned} \right\} \\
 &= \int_{\Phi[H(u_1|u_2)]}^{\Phi[H(u_1)]} \int_{\Phi[H(u_1, u_2)] - \gamma_1}^{+\infty} p(\gamma_1) p(\gamma_2) d\gamma_2 d\gamma_1
 \end{aligned}$$




Fig. 8. Admissible h-SW-MAC region of Case (ii).




Fig. 9. Admissible h-SW-MAC region of Case (iii).

$$\begin{aligned}
 &= \int_{2^{R_c H(P_e)} - 1}^{2^{R_c} - 1} \int_{2^{R_c [1 + H(P_e)] - 1 - \gamma_1}}^{+\infty} p(\gamma_1) p(\gamma_2) d\gamma_2 d\gamma_1 \\
 &= \frac{\Gamma_2}{\Gamma_1 - \Gamma_2} \exp \left[ -\frac{1}{\Gamma_1} (2^{R_c} - 1) \right] \\
 &\quad \cdot \exp \left\{ -\frac{1}{\Gamma_2} [2^{R_c H(P_e) + R_c} - 2^{R_c}] \right\} \\
 &\quad - \frac{\Gamma_2}{\Gamma_1 - \Gamma_2} \exp \left\{ -\frac{1}{\Gamma_1} [2^{R_c H(P_e)} - 1] \right\} \\
 &\quad \cdot \exp \left\{ -\frac{1}{\Gamma_2} [2^{R_c H(P_e) + R_c} - 2^{R_c H(P_e)}] \right\}. \quad (14)
 \end{aligned}$$

It is expected that in this case the helpers most likely have the contribution to the source.

Case (ii):

The admissible rate region in Case (ii) is shown in Fig. 8, which corresponds to the situation where  $H(u_1) < \frac{1}{R_c} C(\gamma_1)$  and  $H(u_2 | u_1) \leq \frac{1}{R_c} C(\gamma_2)$ . The average occurrence probability of the case can be derived mathematically in an explicit form, as

$$\begin{aligned}
 P_{in, case(ii)} &= \Pr \left\{ H(u_1) < \frac{1}{R_c} C(\gamma_1); H(u_2 | u_1) \leq \frac{1}{R_c} C(\gamma_2) \right\} \\
 &= \int_{\Phi[H(u_1)]}^{+\infty} \int_{\Phi[H(u_2|u_1)]}^{+\infty} p(\gamma_1) p(\gamma_2) d\gamma_2 d\gamma_1 \\
 &= \int_{2^{R_c} - 1}^{+\infty} \int_{2^{R_c H(P_e)} - 1}^{+\infty} p(\gamma_1) p(\gamma_2) d\gamma_2 d\gamma_1 \\
 &= \exp \left\{ -\frac{1}{\Gamma_2} [2^{R_c H(P_e)} - 1] \right\} \cdot \exp \left[ -\frac{1}{\Gamma_1} (2^{R_c} - 1) \right]. \quad (15)
 \end{aligned}$$

It is expected that the contributions of both the source and the helper to  $P_{in}$  are large in this case.

Case (iii):

The admissible rate region in Case (iii) is shown in Fig. 9, which corresponds to the situation where  $H(u_1) < \frac{1}{R_c} C(\gamma_1)$  and  $\frac{1}{R_c} C(\gamma_2) < H(u_2 | u_1)$ . When  $\gamma_1 \gg \gamma_2$ , Case (iii) happens most likely. The average occurrence probability of

the case can be derived mathematically in an explicit form, as

$$\begin{aligned}
 P_{in, case(iii)} &= \Pr \left\{ H(u_1) < \frac{1}{R_c} C(\gamma_1); \frac{1}{R_c} C(\gamma_2) < H(u_2 | u_1) \right\} \\
 &= \int_{\Phi[H(u_1)]}^{+\infty} \int_{\Phi(0)}^{\Phi[H(u_2|u_1)]} p(\gamma_1) p(\gamma_2) d\gamma_2 d\gamma_1 \\
 &= \int_{2^{R_c} - 1}^{+\infty} \int_0^{2^{R_c H(P_e)} - 1} p(\gamma_1) p(\gamma_2) d\gamma_2 d\gamma_1 \\
 &= -\exp \left[ -\frac{1}{\Gamma_1} (2^{R_c} - 1) \right] \\
 &\quad \cdot \left\{ \exp \left[ -\frac{1}{\Gamma_2} (2^{R_c H(P_e)} - 1) \right] - 1 \right\}. \quad (16)
 \end{aligned}$$

It is expected that even though the average occurrence probability is very small, however, still the contribution of the helper to  $P_{in}$  does not vanish in this case.

## IV. NUMERICAL RESULTS

### A. Outage Probabilities

Fig. 10 shows the outage probability obtained from explicit expressions shown in subsection III-C and through the Monte-Carlo technique [16]. It is found that the theoretical and Monte-Carlo results are exactly matched.

Fig. 11 compares outage probabilities of SW-MAC and h-SW-MAC with symmetric geometric gains. It is found that outage probabilities of h-SW-MAC is smaller than that of SW-MAC. For example, about 2 dB average SNR reduction can be achieved with the outage probability being  $10^{-3}$ . This is because the admissible rate region is increased with a helper. Also, the joint decoders for both the h-SW-MAC and SW-MAC aim to exploit the correlation between  $u_1$  and  $u_2$ , resulting in the  $2^{nd}$  order diversity. The  $2^{nd}$  order diversity can be more clearly seen in low average SNR value range and high correlation cases (small  $P_e$ ). However, the diversity order converges into one when the average SNR value becomes large. This is because the correlation is not exactly one ( $P_e \neq 0$ ).






Fig. 10. Comparison of the outage probabilities calculated from explicit expressions and the Monte-Carlo technique.




Fig. 11. Comparison of outage probabilities of SW-MAC and h-SW-MAC, where the symmetric geometric gain is assumed.

Fig. 12 and Fig. 13 indicate the outage probability with asymmetric geometric gains, given by

$$P_H = P_S + \alpha, \quad (17)$$

in dB, where  $P_S$  and  $P_H$  represent the geometric gains of the source and the helper links, respectively. The factor  $\alpha$  is set at  $-5$  dB and  $5$  dB in Fig. 12 and Fig. 13, respectively. The results indicate that lower outage probability can be achieved when the geometric gain of the source link is larger than that of the helper link.

### B. Average Occurrence Probabilities of Three Cases

Fig. 14 shows the occurrence probability of Case (i) for  $P_e = 0.1$ . In Case (i),  $\gamma_1 \ll \gamma_2$ , but still intersection happens. Since the entropy of  $u_1$  is fixed to be unity, the larger the average SNR, the less unlikely the Case (i) happens. Hence the occurrence probability due to Case (i) decreases in high average SNR value regions. In this case, since  $\frac{1}{R_c}C(\gamma_1) \leq H(u_1)$ , it is necessary to perform joint decoding at the destination for the successful recovery.




Fig. 12. Comparison of outage probabilities of SW-MAC and h-SW-MAC, where asymmetric geometric gain is assumed, i.e., the geometric gain of the helper-destination link is 5dB lower than that of the source-destination link.




Fig. 13. Comparison of outage probabilities of SW-MAC and h-SW-MAC, where asymmetric geometric gain is assumed, i.e., the geometric gain of the helper-destination link is 5dB higher than that of the source-destination link.

In Case (ii), joint decoding is needed to recover the source  $u_1$  when  $\frac{1}{R_c}C\left(\frac{\gamma_1}{1+\gamma_2}\right) < H(u_1)$ . Since the h-SW region is fixed with the information correlation  $P_e$  given while the capacity increases with the average SNR becomes large, the intersection of the h-SW and the MAC region also increases. As a result, the probability of Case (ii) approaches to unity with the increased average SNR, as shown in Fig. 15.

In Case (iii), since  $\frac{1}{R_c}C\left(\frac{\gamma_1}{1+\gamma_2}\right) \geq H(u_1)$ , the source  $u_1$  can be recovered without joint decoding. However, performing the joint decoding further utilizes the helper information, resulting in even higher probability of successful recovery. The occurrence probability decreases as the average SNR increases, as shown in Fig. 16. Nevertheless, outage does not happen in Case (iii) because the intersection still happens.

The observations of Fig. 14-16 agree with the explanatory sentences shown in subsection III-D. Fig. 14-16 include the difference of the geometric gains between the source and




Fig. 14. Occurrence probability of Case (i) with  $P_e = 0.1$ .




Fig. 15. Occurrence probability of Case (ii) for  $P_e = 0.1$ .




Fig. 16. Occurrence probability of Case (iii) for  $P_e = 0.1$ .

the helper links, 0dB, -5dB, and 5dB as a parameter. Such geometric gain difference makes the performance tendency more clearly.

## V. CORRELATED FADING

The results shown in Section IV are under the scenario that information sequences are transmitted over independent block Rayleigh fading channels. In this section, we investigate outage probabilities of correlated block fading channels. The fading variation correlation of the source-destination and the helper-destination link is defined as  $\rho = \langle h_1 h_2^* \rangle$  with the normalization  $\langle |h_1|^2 \rangle = \langle |h_2|^2 \rangle = 1$ , and  $|\rho| = [0, 1]$  [17]. If the transmission links are independent or fully correlated,  $|\rho| = 0$  and  $|\rho| = 1$ , respectively. With  $|\rho| \neq 0$ , the  $P_{out,1}$  and  $P_{out,2}$  can be calculated by

$$\begin{aligned} P_{out,1} &= \Pr \left\{ \frac{1}{R_c} C(\gamma_1) < H(u_1 | u_2) \right\} \\ &= \int_{\Phi(0)}^{\Phi[H(u_1|u_2)]} \int_{\Phi(0)}^{\Phi(+\infty)} p(\gamma_1, \gamma_2) d\gamma_2 d\gamma_1 \\ &= \int_0^{2^{R_c H(P_e)} - 1} \int_0^{+\infty} p(\gamma_1, \gamma_2) d\gamma_2 d\gamma_1, \end{aligned} \quad (18)$$

and

$$\begin{aligned} P_{out,2} &= \Pr \left\{ \begin{aligned} &H(u_1 | u_2) \leq \frac{1}{R_c} C(\gamma_1) < H(u_1); \\ &\frac{1}{R_c} C(\gamma_1 + \gamma_2) < H(u_1, u_2) \end{aligned} \right\} \\ &= \int_{\Phi[H(u_1|u_2)]}^{\Phi[H(u_1)]} \int_{\Phi(0)}^{\Phi[H(u_1, u_2)] - \gamma_1} p(\gamma_1, \gamma_2) d\gamma_2 d\gamma_1 \\ &= \int_{2^{R_c H(P_e)} - 1}^{2^{R_c} - 1} \int_0^{2^{R_c [1 + H(P_e)]} - 1 - \gamma_1} p(\gamma_1, \gamma_2) d\gamma_2 d\gamma_1, \end{aligned} \quad (19)$$

where  $p(\gamma_1, \gamma_2)$  is the joint probability density function of  $\gamma_1$  and  $\gamma_2$ , given by

$$\begin{aligned} p(\gamma_1, \gamma_2) &= \frac{1}{\Gamma_1 \Gamma_2 (1 - \rho^2)} I_0 \left( \frac{2|\rho| \gamma_1 \gamma_2}{\sqrt{\Gamma_1 \Gamma_2} (1 - |\rho|^2)} \right) \\ &\quad \cdot \exp \left[ -\frac{1}{1 - |\rho|^2} \left( \frac{\gamma_1}{\Gamma_1} + \frac{\gamma_2}{\Gamma_2} \right) \right], \end{aligned} \quad (20)$$

with

$$I_0(x) = \sum_{m=0}^{\infty} \frac{(-1)^m}{(m!)^2} \left( \frac{x}{2} \right)^{2m}, \quad (21)$$

being Bessel function. Hence,  $p(\gamma_1, \gamma_2)$  can be expanded into

$$p(\gamma_1, \gamma_2) = a \sum_{m=0}^M B_m \gamma_1^{2m} \exp \left( c \cdot \frac{\gamma_1}{\Gamma_1} \right) \gamma_2^{2m} \exp \left( c \cdot \frac{\gamma_2}{\Gamma_2} \right), \quad (22)$$

With

$$a = \frac{1}{\Gamma_1 \Gamma_2 (1 - \rho^2)}, \quad (23)$$

$$b = \frac{2|\rho|}{\sqrt{\Gamma_1 \Gamma_2} (1 - |\rho|^2)}, \quad (24)$$

$$c = -\frac{1}{1 - |\rho|^2}, \quad (25)$$

$$B_m = \frac{(-1)^m}{(m!)^2} \left( \frac{b}{2} \right)^{2m}, \quad (26)$$






Fig. 17. Outage probability of correlated MAC and orthogonal transmissions with  $P_e = 0.01$ .

where  $M$  is determined empirically such that the summation in (19) converges. In this article,  $M = 3$  is found to be enough. Then,  $P_{out,1}$  and  $P_{out,2}$  can be calculated by

$$P_{out,1} = a \sum_{m=0}^M \left\{ B_m \left[ \int_0^{2^{R_c H(P_e)-1}} \gamma_1^{2m} \exp\left(c \cdot \frac{\gamma_1}{\Gamma_1}\right) d\gamma_1 \right] \cdot \left[ \int_0^{+\infty} \gamma_2^{2m} \exp\left(c \cdot \frac{\gamma_2}{\Gamma_2}\right) d\gamma_2 \right] \right\}, \quad (27)$$

and

$$P_{out,2} = a \sum_{m=0}^M \left\{ B_m \int_{2^{R_c H(P_e)-1}}^{2^{R_c}-1} \int_0^{2^{R_c[1+H(P_e)]-1-\gamma_1}} P d\gamma_2 d\gamma_1 \right\}, \quad (28)$$

with

$$P = \gamma_2^{2m} \exp\left(c \cdot \frac{\gamma_2}{\Gamma_2}\right) \gamma_1^{2m} \exp\left(c \cdot \frac{\gamma_1}{\Gamma_1}\right). \quad (29)$$

Fig. 17 shows for  $P_e = 0.01$  the outage probability with the fading variation correlation  $|\rho|$  as a parameter. The outage probabilities of the MAC and the orthogonal transmissions [18] are indicated by the dotted and solid curves, respectively. The  $2^{nd}$  order diversity can be achieved in low average SNR value range and the outage curves finally approach the  $1^{st}$  order diversity as the average SNR increases because  $P_e \neq 0$ . The larger the  $|\rho|$  value, the smaller the value of the average SNR is, where the  $2^{nd}$  order diversity can be achieved. Also, the orthogonal transmission can achieve lower outage probability, but the difference is very minor.

## VI. CONCLUSIONS

In this article, the system of one source with one helper transmitted over a block Rayleigh fading MAC has been investigated. For successful transmission, the transmission rate should satisfy both the h-SW and MAC regions, which is a sufficient condition. Outage probabilities with different factors, including information correlations, geometric gains and channel variation correlations, have been provided. To have

in-depth insights of the contributions of three cases to the successful transmission, we also derived the explicit expressions of the occurrence probabilities of the three cases.


It has been shown that compared with SW-MAC, the outage probability further reduces by h-SW-MAC. Numerical results indicated that the  $2^{nd}$  order diversity can be achieved in the low average SNR value range in the case information sequences transmitted from the source and the helper are highly correlated. Lower outage can be achieved if the geometric gain of the source link is larger than that of the helper link. Most significantly, with MAC, the throughput efficiency can be twice as large as that with orthogonal transmissions. The numerical analysis shown in this article provide a theoretical basis for one source with one helper transmitted over a block Rayleigh fading MAC. The scenarios of one source with multiple helpers as well as multiple sources with one helper are left as a future study.

## REFERENCES


- [1] D. Ciuonzo and P. S. Rossi, *Data Fusion in Wireless Sensor Networks: A Statistical Signal Processing Perspective*. Edison, NJ, USA: IET, 2019.
- [2] M. Cheng, M. R. K. Aziz, and T. Matsumoto, "Integrated factor graph algorithm for DOA-based geolocation and tracking," *IEEE Access*, vol. 8, pp. 49989–49998, 2020.
- [3] M. Cheng, M. R. K. Aziz, and T. Matsumoto, "A DOA-based factor graph technique for 3D multi-target geolocation," *IEEE Access*, vol. 7, pp. 94630–94641, 2019.
- [4] R. Rajesh and V. Sharma, "Transmission of correlated sources over a fading multiple access channel," in *Proc. 46th Annu. Allerton Conf. Commun., Control, Comput.*, Sep. 2008, pp. 858–864.
- [5] X. Zhou, X. He, M. Juntti, and T. Matsumoto, "Outage probability of correlated binary source transmission over fading multiple access channels," in *Proc. IEEE 16th Int. Workshop Signal Process. Adv. Wireless Commun. (SPAWC)*, Stockholm, Sweden, Jun. 2015, pp. 96–100.
- [6] J. He, "Performance of MIMO and nonorthogonal transmission in lossy forward relay networks," *Acta Univ. Oul. C* 677, 2018.
- [7] X. Zhou, M. Cheng, X. He, and T. Matsumoto, "Exact and approximated outage probability analyses for decode-and-forward relaying system allowing intra-link errors," *IEEE Trans. Wireless Commun.*, vol. 13, no. 12, pp. 7062–7071, Dec. 2014.
- [8] A. El Gamal and Y. H. Kim, *Network Information Theory*. Cambridge, U.K.: Cambridge Univ. Press, 2011.
- [9] K. Anwar and T. Matsumoto, "Accumulator-assisted distributed turbo codes for relay systems exploiting source-relay correlation," *IEEE Commun. Lett.*, vol. 16, no. 7, pp. 1114–1117, Jul. 2012.
- [10] C. E. Shannon, "A mathematical theory of communication," *Bell Syst. Tech. J.*, vol. 27, no. 3, pp. 379–423, Jul./Oct. 1948.
- [11] T. Cover and J. Thomas, *Elements of Information Theory*. Hoboken, NJ, USA: Wiley, 2006.
- [12] J. Garcia-Frias and Y. Zhao, "Near-Shannon/Slepian-Wolf performance for unknown correlated sources over AWGN channels," *IEEE Trans. Commun.*, vol. 53, no. 4, pp. 555–559, Apr. 2005.
- [13] M. Cheng, K. Anwar, and T. Matsumoto, "Outage probability of a relay strategy allowing intra-link errors utilizing Slepian-Wolf theorem," *EURASIP J. Adv. Signal Process.*, vol. 2013, no. 1, pp. 22–34, Dec. 2013.
- [14] C. E. Shannon, "Coding theorems for a discrete source with a fidelity criterion," *IRE Nat. Conv. Rec.*, vol. 4, no. 1, pp. 142–163, 1959.
- [15] M. Schwartz, W. R. Bennett, and S. Stein, "Communication systems and techniques," *IEEE Commun. Mag.*, vol. 34, no. 5, pp. 9–10, May 1996.
- [16] H. Kahn, "Use of different Monte-Carlo sampling techniques," in *Proc. Symp. Monte-Carlo Methods Wiley*, 1956, pp. 24–27.
- [17] S. Qian, J. He, M. Juntti, and T. Matsumoto, "Fading correlations for wireless cooperative communications: Diversity and coding gains," *IEEE Access*, vol. 5, pp. 8001–8016, 2017.
- [18] M. Cheng, K. Anwar, and T. Matsumoto, "On the duality of source and channel correlations: Slepian-Wolf relaying viewpoint," in *Proc. IEEE Int. Conf. Commun. Syst. (ICCS)*, Nov. 2012, pp. 388–392.



**Shulin Song** received the B.S. degree in communication engineering from the Xi'an University of Posts and Telecommunications, Xi'an, China, in 2018. She is currently pursuing the M.S. degree with the Japan Advanced Institute of Science and Technology (JAIST), Ishikawa, Japan. Her research interests include network information theory, cooperative wireless communications, and non-orthogonal multiple access.



**Xiaobo Zhou** (Senior Member, IEEE) received the B.Sc. degree in electronic information science and technology from the University of Science and Technology of China (USTC), Hefei, China, in 2007, the M.E. degree in computer application technology from the Graduate University of Chinese Academy of Science (GUCAS), Beijing, China, in 2010, and the Ph.D. degree from the School of Information Science, Japan Advanced Institute of Science and Technology (JAIST), Ishikawa, Japan, in 2013. He is currently an Associate Professor with the School of Computer Science and Technology, Tianjin University. Prior to that, he was a Researcher with the Centre for Wireless Communications, University of Oulu, Finland, from 2014 to 2015. His research interests include joint source-channel coding, cooperative wireless communications, network information theory, cloud computing, and software defined networking.



**Meng Cheng** received the B.Eng. degree in telecommunication engineering from the Anhui University of Technology, Anhui, China, in 2009, the M.Sc. (Hons.) degree in wireless communications from the University of Southampton, Southampton, U.K., in 2010, and the Ph.D. degree in information science from the Japan Advanced Institute of Science and Technology (JAIST), Ishikawa, Japan, in 2014. He has served as a 5G Research Engineer with the Shanghai Research Center, Huawei Technologies Company, Ltd., from 2014 to 2017. After that, he returned to JAIST as a Postdoctoral Researcher. His research interests include network information theory, non-orthogonal multiple access (NOMA), iterative coding/decoding, and wireless geolocation techniques.

company, Ltd., from 2014 to 2017. After that, he returned to JAIST as a Postdoctoral Researcher. His research interests include network information theory, non-orthogonal multiple access (NOMA), iterative coding/decoding, and wireless geolocation techniques.



**Tad Matsumoto** (Fellow, IEEE) received the B.S. and M.S. degrees in electrical engineering under the supervision by Prof. Shin-Ichi Takahashi and the Ph.D. degree in electrical engineering under the supervision by Prof. Masao Nakagawa from Keio University, Yokohama, Japan, in 1978, 1980, and 1991, respectively. He joined Nippon Telegraph and Telephone Corporation (NTT) in April 1980. Since he engaged in NTT, he was involved in a lot of research and development projects, all for mobile wireless communications systems. In July 1992, he transferred to NTT DoCoMo, where he researched Code-Division Multiple-Access techniques for Mobile Communication Systems. In April 1994, he transferred to NTT America, where he served as a Senior Technical Advisor of a joint project between NTT and NEXTEL Communications. In March 1996, he returned to NTTDoCoMo, where he served as the Head of the Radio Signal Processing Laboratory until August 2001. He has worked on adaptive signal processing, multiple-input multiple-output turbo signal detection, interference cancellation, and spacetime coding techniques for broadband mobile communications. In March 2002, he moved to University of Oulu, Finland, where he served as a Professor with the Centre for Wireless Communications. In 2006, he served as a Visiting Professor with the Ilmenau University of Technology, Ilmenau, Germany, funded by the German MERCATOR Visiting Professorship Program. Since April 2007, he has been serving as a Professor at the Japan Advanced Institute of Science and Technology (JAIST), Japan, while also keeping a cross-appointment position at the University of Oulu. He has led a lot of projects funded by the Academy of Finland, European FP7, the Japan Society for the Promotion of Science, and the Japanese private companies. Prof. Matsumoto has been appointed as a Finland Distinguished Professor from January 2008 to December 2012, funded by the Finnish National Technology Agency (Tekes) and Finnish Academy, under which he preserves the rights to participate in and apply to European and Finnish national projects. He is a member of IEICE. He has been an IEEE Vehicular Technology Distinguished Speaker since July 2016. He was a recipient of the IEEE VTS Outstanding Service Award in 2001, the Nokia Foundation Visiting Fellow Scholarship Award in 2002, the IEEE Japan Council Award for Distinguished Service to the Society in 2006, the IEEE Vehicular Technology Society James R. Evans Avant Grade Award in 2006, the Thuringen State Research Award for Advanced Applied Science in 2006, the 2007 Best Paper Award of Institute of Electrical, Communication, and Information Engineers of Japan in 2008, the Telecom System Technology Award by the Telecommunications Advancement Foundation in 2009, the IEEE COMMUNICATION LETTERS Exemplary Reviewer in 2011, the Nikkei Wireless Japan Award in 2013, the IEEE VTS Recognition for Outstanding Distinguished Lecturer in 2016, and the IEEE TRANSACTIONS ON COMMUNICATIONS Exemplary Reviewer in 2018.



**Jiguang He** (Member, IEEE) received the B.Eng. degree from the Harbin Institute of Technology, Harbin, China, in 2010, the M.Sc. degree from Xiamen University, Xiamen, China, in 2013, and the D.Sc. degree from the University of Oulu, Oulu, Finland, in 2018, all in communications engineering. From September 2013 to March 2015, he was with the Key Laboratory of Millimeter Waves, City University of Hong Kong, and conducting research on channel tracking over millimeter wave MIMO systems. Since

June 2015, he has been with the Centre for Wireless Communications (CWC), University of Oulu. His research interests include cooperative communications, network information theory, joint source and channel coding, and distributed compressive sensing.