## **JAIST Repository**

https://dspace.jaist.ac.jp/

Title	EXPERIMENTAL EVALUATION OF TRELLIS DECODING PERFORMANCE ON LINEAR BLOCK CODES IN DIGITAL MOBILE RADIO
Author(s)	Matsumoto, T.
Citation	Electronics Letters, 24(17): 1107-1108
Issue Date	1988-08-18
Туре	Journal Article
Text version	publisher
URL	http://hdl.handle.net/10119/4802
Rights	Copyright (c)1988 IEEE. Reprinted from Electronics Letters, 24(17), 1988, 1107-1108. This material is posted here with permission of the IEEE. Such permission of the IEEE does not in any way imply IEEE endorsement of any of JAIST's products or services. Internal or personal use of this material is permitted. However, permission to reprint/republish this material for advertising or promotional purposes or for creating new collective works for resale or redistribution must be obtained from the IEEE by writing to pubs-permissions@ieee.org. By choosing to view this document, you agree to all provisions of the copyright laws protecting it.
Description	



our OA, but the frequency spacing  $\Delta f_2$  between  $P_1$  and  $P_2$  should exceed 20 GHz to avoid a complicated NDFWM spectrum. A disadvantage of the method is the necessity of an optical filter. For future applications we consider some modifications and extensions of the frequency conversion technique described here. Firstly,  $P_1$  and  $P_2$  need not be copropagating waves with the same polarisation. This may offer some advantages with respect to gain saturation of the OA and channel filtering. Secondly,  $S_{in}$  may be converted simultaneously to several frequencies within the bandwidth of the OA. The different converted channels can independently turned on and off with the powers of the different pump waves  $P_2$ .

Acknowledgment: This work was supported by the Bundesministerium für Forschung und Technologie of the Federal Republic of Germany under contract TK 0438. The authors alone are responsible for the contents.

G. GROSSKOPF 18th July 1988 R. LUDWIG H. G. WEBER Heinrich-Hertz-Institut für Nachrichtentechnik Berlin GmbH

Einsteinufer 37, D-1000 Berlin 10, Federal Republic of Germany

## References

- BRAUN, R. P., and STREBEL, B.: 'Optical nonlinearities in coherent multichannel networks'. IQEC '88, Tokyo, 1988
  INOUE, K., MUKAI, T., and SAITOH, T.: 'Nearly degenerate four-wave
- 2 INOUE, K., MUKAI, T., and SAITOH, T.: 'Nearly degenerate four-wave mixing in a travelling-wave semiconductor laser amplifier', Appl. Phys. Lett., 1987, 51, pp. 1051-1053
- 3 WAARTS, R. G., GROSSKOPF, G., LUDWIG, R., and WEBER, H. G.: 'Fourwave mixing in semiconductor laser media'. OSA 1987 annual meeting, Oct. 1987, Rochester, Postdeadline paper PD 15
- 4 GROSSKOPF, G., LUDWIG, R., WAARTS, R. G., and WEBER. H. G.: 'Fourwave mixing in a semiconductor laser amplifier', *Electron. Lett.*, 1988, 24, pp. 31-32
- 5 JOPSON, R. M., DARCIE, T. E., GAYLIARD, K. T., KU, R. T., TENCH, R. E., RICE, T. C., and OLSSON, N. A.: 'Measurement of carrier-density medicated intermodulation distortion in an optical amplifier', *Electron. Lett.*, 1987, 23, pp. 1394–1395

## EXPERIMENTAL EVALUATION OF TRELLIS DECODING PERFORMANCE ON LINEAR BLOCK CODES IN DIGITAL MOBILE RADIO

Indexing terms: Digital communication systems, Codes and coding, Mobile radio systems, Decoding

Word error rate (WER) performance with soft decision decoding of linear block codes using a trellis is investigated in a Rayleigh fading channel. The signal envelopes corresponding to each bit in a received block are sampled and used for estimating the reliability of the bit. The WER performance is evaluated via laboratory experiments using Hamming (7, 4) code. A great improvement in WER performance can be achieved over conventionally-used minimum distance decoding.

Introduction: In land mobile radio, the digital signal transmission performance is severely degraded owing to multipath Rayleigh fading.<sup>1</sup> Error control coding, in which random error correcting block codes, such as BCH codes, have been widely used, is an effective technique for reducing fading effects.<sup>2</sup> It is well known that soft decision decoding can achieve better performance than conventional minimum distance decoding.<sup>3–5</sup> This is because soft decision decoding uses not only the algebraic redundancy of the code but also the channel measurement information (CMI) for estimating reliability of received bits, while minimum distance decoding uses only the redundancy. However, most soft decision algorithms are complex, and are applicable only to restricted classes of codes. Wolf<sup>2</sup> has shown that the well known Viterbi algorithm, in which the decoding complexity is greatly reduced,

ELECTRONICS LETTERS 18th August 1988 Vol. 24 No. 17

can be applied to decoding of linear block codes using a trellis.

This letter presents a method for applying trellis decoding of linear block codes to a Rayleigh fading channel. The received signal envelopes corresponding to each bit of the code are sampled and used as the CMI. The metric values corresponding to each node of the trellis are derived from the CMI. The word error rate (WER) performance of trellis decoding and minimum distance decoding with 1 bit error correction for Hamming (7, 4) code are investigated via laboratory experiments. These decoding algorithms are applied to 16 kbit/s signal transmission using GMSK modulation and frequency detection. The experimental results show that the WER performance is greatly improved over minimum distance decoding in an experimentally-simulated Rayleigh fading channel when the trellis decoding is used.

Trellis decoding using received signal envelopes: Consider an (N, K) linear block code. Let the *i*th column vector of the parity check matrix be denoted as  $h_i$  ( $i = 1 \sim N$ ). For a codeword  $X_j = (X_{j1}, \ldots, X_{jN})$ , in which  $X_{ji}$  is an element of a Grois field GF (q), the node  $S_t$  is defined as

$$S_k = \sum_{i=1}^k X_{ji} h_i \tag{1}$$

where  $k = 1 \sim N$  and  $S_0 = (0 \ 0 \ \dots \ 0)^t$ . The series  $S_1, S_2, \dots, S_N$  is the locus of the codeword  $X_j$ . The set of all loci described by the series for all codewords constitutes a trellis. A trellis for Hamming (7, 4) code is shown in Fig. 1.



Fig. 1 Trellis for Hamming (7, 4) code

The metric value of the kth node for the codeword  $X_j$  is given by

$$L_k(X_j) = \sum_{i=1}^k \log f_i \tag{2}$$

where  $k = 1 \sim N$ , and  $f_i$  is the likelihood ratio of the hard decision result of the  $X_i$ s ith bit. The  $f_i$  value is given by

$$f_{i} = \begin{cases} p_{i}/(1 - p_{i}) \dots Y_{i} \neq X_{ji} \\ (1 - p_{i})/p_{i} \dots Y_{i} = X_{ji} \end{cases}$$
(3)

where  $p_i$  is the error probability of the *i*th bit and  $Y_i$  is the decision result for the bit. The sampled value of the received signal envelope is used as the CMI to estimate the bit error probability. For example, the bit error probability  $p_i$  for non-coherent FSK is estimated by  $p_i = (1/2) \cdot \exp(-\gamma_i/2)$ , where  $\gamma_i = R_i^2/2$  is the signal/noise power ratio (SNR) with  $R_i$  the envelope sample of the *i*th bit and  $N_0$  the average in-band noise power.

The Viterbi algorithm can be applied to the trellis. When the kth node of the codeword  $X_i$  is the same as that of  $X_j$ , the metric values of these codewords,  $L_k(X_i)$  and  $L_k(X_j)$ , are compared, and the codeword with smaller value is discarded. In all the nodes which have two entering branches, the codeword of greater metric value is selected. In the *n*th node, the most likely of the codewords is selected and delivered as the output of decoding.

Laboratory experiment results: The trellis decoding algorithm was applied to 16 kbit/s signal transmission using a GMSK

1107

modulation and frequency-detection system. Laboratory experiments were conducted for the Hamming (7, 4) code. A 16 kbit/s bit stream of the coded data was interleaved, differentially encoded, and fed to the IF stage GMSK-modulator. The differential encoding was necessary to apply a 1/2-bit offset decision rule<sup>6</sup> in the receiver to avoid causing error propagation. A Gaussian lowpass filter with a 3dB bandwidth of 8kHz was used for premodulation band limitation. The fading GMSK signal was generated by a Rayleigh fading simulator operating on a 90 MHz band. The maximum Doppler frequency  $f_D$  of the fading simulator was set at 120 Hz, corresponding to a typical vehicle speed of 64 km/h for the RF frequency of a 2GHz band. The bit interleaving degree  $M_i$  was set at 64, where the envelope samples in a received block are considered statistically independent. A limiter-discriminator type receiver and 1/2-bit offset decision were used \*

An approximately Gaussian ceramic filter with a centre frequency of 455kHz and a 3dB bandwidth of 12kHz was adopted for the predetection bandpass filter. The frequency discriminator output was lowpass-filtered by another Gaussian filter with 3 dB bandwidth of 8 kHz for postdetection noise reduction. The filter output was fed to a 1/2-bit offset decision circuit, and the data stream regenerated.

The logarithmically-compressed IF signal was envelopedetected. The envelope detector output was lowpass-filtered by a four-pole Butterworth filter with a 3dB bandwidth of 1 kHz. The filter output was sampled and then value-limited in the  $0 \sim 20 \, dB$  range using an *n* bit A/D convertor with resolution n of  $0 \sim 6$ . A great amount of (n + 1)-bit data segments consisting of regenerated data and the envelope sample were stored for later processing. The trellis decoding algorithm was performed using the stored data.

The experimental WERs against the A/D-convertor resolution *n* is shown in Fig. 2 for  $M_i = 64$ , when the channel bit error rate (BER) was  $1.4 \times 10^{-2}$ . The WER performance improvement levels off when  $n \ge 3$ . The experimental WERs against the channel BERs are shown in Fig. 3 for trellis decoding and minimum distance decoding with 1 bit error correc-



Fig. 2 Experimental WER against resolution of n-bit A/D conversion Hamming (7, 4) code;  $f_D = 120 \text{ Hz}$ ;  $M_i = 64$ ; BER =  $1.4 \times 10^{-2}$ 

\* Limiter-discriminator detection is widely used for FSK signal reception. The BER for FSK with a limiter-discriminator can be appro imated by  $(1/2) \exp(-\alpha y)$ , in which parameter  $\alpha$  is experimentally obtained. Hence, this algorithm can be applied.

tion for  $M_i = 64$  and n = 3. A great improvement in WER performance is obtained over minimum distance decoding when trellis decoding is used. The BER of (N, K) block code



Hamming (7, 4) code;  $f_D = 120 \text{ Hz}$ ;  $M_i \approx 64$ ; 3 bit A/D conversion

Simulation ●●● Minimum distance decoding 000 Trellis decoding

after decoding is estimated from the WER by the following:7 BER after decoding  $\approx$  WER  $\times 2^{K-1}/(2^{K}-1)$ . The BER after the trellis decoding for the Hamming (7, 4) code is about  $1 \times 10^{-3}$  while that after minimum distance decoding is about  $5 \times 10^{-3}$ , when the channel BER is  $2 \times 10^{-2}$ . The computer simulation results of WER are also plotted in the Figure. A little degradation from the simulation results is observed in the experimental WERs. Further study will clarify the reason for this degradation.

Conclusion: WER performance with trellis decoding of linear block codes was investigated in a Rayleigh fading channel. The Hamming (7, 4) code was used for the WER performance evaluation via laboratory experiments. The trellis decoding algorithm was applied to a 16 kbit/s signal transmission using GMSK modulation and a frequency detection system. A great improvement in WER performance was obtained over conventional minimum distance decoding when the bit interleaving degree = 64 and the maximum Doppler frequency = 120 Hz.

T. MATSUMOTO 15th April 1988 NTT Radio Communication Systems Laboratories PO Box 8, Yokosuka 238, Japan

## References

- CLARKE, R. H.: 'A statistical theory of mobile-radio reception', Bell 1
- Syst. Tech. J., 1968, 47, pp. 957–1000 MaBEY, P. J.: 'Mobile radio data transmission-control', *IEEE Trans.*, 1978, VT-27, pp. 99–109 2 -coding for error
- FORNEY, G. D., JUN., 'Generalized minimum distance decoding', *IEEE Trans.*, 1966, **IT-12**, pp. 125–131
- CHASE, D.: 'A class of algorithms for decoding block codes with channel measurement information', IEEE Trans., 1972, IT-18, pp. 170-182
- WOLF, J. K.: 'Efficient maximum likelihood decoding of linear block codes using a trellis', IEEE Trans., 1978, IT-24, pp. 76-80 OHNO, K., and ADACHI, F.: 'Half-bit offset decision frequency detec-
- tion of differentially encoded GMSK signals', Electron. Lett., 1987, 23, pp. 1311-1312
- TORRIERI, D. J.: 'The information-bit error rate for block codes', IEEE Trans., 1984, COM-32, pp. 474-476

ELECTRONICS LETTERS 18th August 1988 Vol. 24 No. 17

1108