JAIST Repository

https://dspace.jaist.ac.jp/

Title	FORWARD LINK CAPACITY LIMIT OF CODED FFH/CDMA MULTIUSER MOBILE RADIOS
Author(s)	Kawahara, T.; Matsumoto, T.
Citation	Electronics Letters, 27(21): 1918-1919
Issue Date	1991-10-10
Туре	Journal Article
Text version	publisher
URL	http://hdl.handle.net/10119/4806
Rights	Copyright (c)1991 IEEE. Reprinted from Electronics Letters, 27(21), 1991, 1918-1919. This material is posted here with permission of the IEEE. Such permission of the IEEE does not in any way imply IEEE endorsement of any of JAIST's products or services. Internal or personal use of this material is permitted. However, permission to reprint/republish this material for advertising or promotional purposes or for creating new collective works for resale or redistribution must be obtained from the IEEE by writing to pubs-permissions@ieee.org. By choosing to view this document, you agree to all provisions of the copyright laws protecting it.
Description	



tion by direct reaction between tungsten and silicon'. Appl. Surf. Sci., 1989, 38, pp. 486-194

- 4 PAILHUN, P., HSEH, N., GEIPEL, JR, H. J., and SLUSSER, G. J.: Dopant diffusion in tungsten silicide', J. Appl. Phys., 1982, 53, (4), pp. 3059-3062
- 5 JAHNEL, F., BIERSACK, J., CROWDER, B. L., D'HEURLE, F. M., FINK, D., ISAAC, R. D., LUCCHESE, C. J., and PETERSSON, C. S.: 'The behavior of boron (also arsenic) in bilayers of polycrystalline silicon and tungsten dislicide', J. Appl. Phys., 1982, 53, (11), pp. 7372-7376

FORWARD LINK CAPACITY LIMIT OF CODED FFH/CDMA MULTIUSER MOBILE RADIOS

Indexing terms: Mobile radio systems, Codes and coding

The theoretical limit of the forward link (base to mobile) user capacity of fast frequency hopping code division multiple access (FFH/CDMA) mobile communication systems with error correction coding is investigated. The channel cutoff rate of coded FFH/CDMA channels is calculated and the optimal code rate that maximises the user capacity is determined. It is shown that with deletion-free transmission, the frequency efficiency of an FFH/CDMA channel coded at the optimal code rate is 47% higher than without coding.

Introduction: Since Goodman et al. presented a fast frequency hopping code division multiple access (FFH/CDMA) system and applied it to mobile/personal radio communications in 1980,¹ it has attracted much attention, and several performance improvements have been made.²⁻⁴ In the FFH/ CDMA system, the same frequency band is shared by many users and the transmitted symbol is extracted from the detection matrix indicating detected frequencies.

It was shown in Reference 1 that with deletion-free transition (all the errors are due to the interference from other users), 209 forward link (base to mobile) users transmitting 32 kbit/s speech (or data) could be accommodated with a bit error rate (BER) less than or equal to 10^{-3} , using a 20 MHz bandwidth. Reference 2 showed that by algebraically structuring the address sequence, the user capacity could be further increased by about 60%. Another power strategy is to use coding for error protection. Several practical codes suitable for FFH/CDMA channels have been proposed,^{4,5} and their decoding performances have been analysed taking into account the desired signal deletions and interference insertions.

This Letter investigates the theoretical limit of the forward link user capacity of FFH/CDMA mobile communication systems with coding. The optimal code rate that maximises the forward link user capacity is then determined from the channel cutoff rate.

System model: Fig. 1 shows the system model to be analysed. The input bit stream to be transmitted is stored in a K bit shift register and segmented into K bit symbols. The K bit symbol sequence is then encoded into the coded symbol sequence of an (n, k) code defined over the Galois field of

 $GF(2^{\kappa})$. The coded symbol with symbol duration of T is then divided in time into L chips, each of which has a chip duration of T/L, and a random address sequence with rate L/T is added to the chip sequence with modulo- 2^{κ} . The 2^{κ} frequencies are available for the forward link transmission, and one, corresponding to a chip modified by the random address, is transmitted over the chip interval. Prior to transmission, the chip sequence is fed to an OR logic circuit to accommodate the chips of other users hitting the same frequency slot. In the receiver, the received power of each of the 2^{κ} frequencies is detected by an energy detector. Hard decision is used for detection. Both the transmitter and the receiver know the predetermined address sequence, and the address sequence is then added with modulo- 2^{κ} to the detection matrix which indicates received detected frequencies. The detection matrix is the input to the decoder, and the transmitted symbol is estimated and delivered to each user as the channel output.

Channel cutoff rate: The channel cutoff rate R_0 represents one of the upper bounds of the information bit rate. With bit rate $R(\leq R_0)$ information bit/channel symbol, the input information can be transmitted with $BER \leq e^{-N(RO-R)}$ where N is the code length (from this feature, communication with an information bit rate of $R \leq R_0$ is referred to as 'reliable communication'). R_0 characterises only the coding channel, and is independent of the specific code employed.

Several of the formulas required to analyse the channel cutoff rate and user capacity are shown in Table 1 of Reference 1, and they will be used in this Letter without derivation. The average probability p_1 of insertion due to interference is given by

$$p_I = [1 - (1 - 2^{-K})^{M-1}](1 - p_D)$$
(1)

where p_D is the average deletion probability that the transmitted frequency is not detected by the energy detector. p_D is expressed as

$$p_D = 1 - \exp\left\{\frac{-\beta^2}{2(1+\Gamma)}\right\}$$
 (2)

where Γ is the average received signal to noise power ratio (SNR), and β is the threshold normalised with respect to the receiver noise power.⁶ Another factor that affects the value of p_I is the false alarm probability p_F , which is expressed as a function of β , and was taken into account in Reference 1. However, because for large Γ values p_D is approximately expressed as a function of β^2/Γ , p_D can be set at any value independently of p_F . Thus, we assume $p_F = 0$.

The received dehopped frequencies are represented in the detection matrix Y including entries from the desired signal and interferers. If neither insertion nor delection occur, Y has a row corresponding to the transmitted 2^{K} -ary FSK symbol. Therefore, it is reasonable that the number of the entries in the *i*th row of the detection matrix Y is used as the metric for the *i*th symbol x_i of the 2^{K} -ary FSK.

The Chernoff bound of the metric difference $D(\lambda)$ is given by

$$D(\lambda) = E[e^{\lambda \{m(\mathbf{x}_j, \mathbf{Y}) - m(\mathbf{x}_i, \mathbf{Y})\}} | \mathbf{x}_i]_{\mathbf{x}_i \neq \mathbf{x}_i}$$
(3)

where $m(x_i, Y)$ and $m(x_j, Y)$ denote the metric values for the ith and jth symbols of the 2^{K} -ary FSK, respectively; λ is the



Fig. 1 System model

1918

ELECTRONICS LETTERS 10th October 1991 Vol. 27 No. 21

Chernoff parameter and E denotes ensemble average. Assuming that x_i is transmitted and that insertion and deletion occur randomly, $D(\lambda)$ becomes

 $D(\lambda) = \sum_{s=0}^{L} e^{-\lambda s} {\binom{L}{s}} (1 - P_D)^s P_D^{L-s} \sum_{t=0}^{L} e^{\lambda t} {\binom{L}{t}} P_t^t (1 - P_I)^{L-t}$

where $\binom{A}{B}$ denotes the binomial coefficient.

Because an FFH/CDMA channel is a symmetric channel, the channel cutoff rate R_0 is given by

$$R_0 = K - \log_2\{1 + (2^K - 1)D\}$$
(5)

where

л

$$P = \min_{\lambda \in \Omega} D(\lambda) \tag{6}$$

Fig. 2 shows the calculated channel cutoff rate R_0 against the number M of users sharing the FFH/CDMA channel for L = 19 and K = 8 with p_D as a parameter. The minimum value of $D(\lambda)$ with respect to λ was determined numerically. It is found from Fig. 2 that R_0 approaches its maximum value of 8(-K) as M decreases. As p_p increases, M must be decreased further to ensure the maximum value of R_0 . This is implied because R_0 is dominated by desired signal deletions rather than interference insertions.



Fig. 2 Channel cutoff rate against user capacity FFH/CDMA K = 8L = 19

Optimal code rate: The number of users can be increased by using a low rate code with large error correction capability. However, low rate codes increase the transmission bandwidth. Because of this tradeoff, there exists an optimum code rate that maximises the user capacity normalised by the code rate. The channel cutoff rate R_0 is expressed as a function of the number of the users *M*. Therefore, with coding rate r = R/K, if M satisfies

> $M \leq R_0^{-1}(rK)$ (7)

reliable communications are possible for all the M users via the coded FFH/CDMA channel having a bandwidth 1/r times larger than the original uncoded FFH/CDMA channel. Fig. 3 shows the number of the users normalised by the code rate Mr against code rate r for L = 19 and K = 8 with p_D as a parameter. It is found from Fig. 3 that for all values of p_p , Mr is maximised at a code rate of about 0.85. If $p_p = 0$, the coded FFH/CDMA channel can accommodate 308 users and reliable communications are possible, using the same bandwidth as that of the uncoded system. This user capacity is 1.47 times larger than that of the uncoded system with the same L and Kvalues.1

Conclusion: The channel cutoff rate of the coded FFH/CDMA channel was calculated and the optimal code rate that maximises the user capacity was determined. It has been shown

ELECTRONICS LETTERS 10th October 1991 Vol. 27 No. 21

that the optimal code rate for 256-ary FSK with 19 hop/ symbol is about 0.85. With deletion-free transmission, the capacity is 359 users (normalised capacity is 308 users), and



Fig. 3 Normalised user capacity against code rate FFH/CDMA

$$K = 8$$

 $L = 19$

T. 1 **T**. 1

(4)

reliable communication for all users is made possible by hard decision maximum likelihood decoding. This coded FFH/ CDMA system is 47% more frequency-efficient than an uncoded system.

2nd August 1991

NT atories 1-2356, Take, Yokosukashi, Kanagawa-ken, 238, Japan

References

- GOODMAN, D. J., HENRY, P. S., and PRABHU, V. K.: 'Frequencyhopped multilevel FSK for mobile radio', Bell Syst. Tech. J, Sep-tember 1980, 59, pp. 1257-1275
- TIMOR, U.: 'Multistage decoding of frequency-hopped FSK systems', *Bell Syst. Tech. J.*, April 1981, **60**, pp. 471–483 HEALY, T. J.: 'Coding and decoding for code division multiple user 2
- communication system', IEEE Trans., 1985, COM-33, (4), pp. 310-316
- KIM, S. W., and STARK, W.: 'Optimum Reed-Solomon codes for frequency-hopping spread-spectrum multiple-access communica-tion system', *IEEE Trans.*, 1989, COM-37, (2), pp. 138–144 VITERBI, A. J.: 'A processing satellite transponder for multiple
- Access by low-rate mobile users'. Dig. Satellite Commun. Conf. Montreal, P. Q., Canada, 23rd-25th October 1978, pp. 166-174 SCHWARTZ, M., BENNETT, W. R., and STEIN, S.: 'Communication systems and techniques' (McGraw-Hill, 1966), pp. 396-411

AUTOMATIC GAIN CONTROLLED **OSCILLATING AMPLIFIER**

Indexing terms: Amplifiers, Automatic control, Oscillators, Circuit design

An amplifier based on an injection-locked surface transverse wave oscillator is described and characterised. It is shown to exhibit automatic gain control. Its noise performance is discussed for the case of a 2 Mbit/s binary phase shift key signal.

Introduction: Traditional amplifier design techniques restrict the onset of oscillations by avoiding the corresponding loop phase and gain conditions. This is often accomplished by designing the circuit so that the k factor, a figure of merit that ensures unconditional stability, is greater than 1. If unconditional stability cannot be achieved, or if it requires too many compromises on the amplifier performance, then conditional stability is sought.¹

1919